ELECTRONIC MODULES FOR BRAKES

Half-Wave Rectifier - Slim Collection

32 07102B53

Thanks to its extremely compact design, the overexcitation rectifier can be installed in very restricted space. The module features a central bore for screw fixing inside the terminal box. It can also be installed by using an adhesive pad. These types of Slim Collection AC operate as a half-wave/bridge rectifier with integrated electronic fast turn-off through voltage
detection (depending on type).

Features

- Very small design
- Cost-effective
- Versatile options for assembly and connection through central hole
- Overexcitation function
- Integrated fast shutdown
- Energy savings up to 75%
- Dimensions (LxWxH): 60x24x19 mm

© Kendrion N.V.

DESCRIPTION	VALUE
Rectifier type	Half-Wave-Rectifier
Input voltage range	0 bis 240 V
Max. current	0,5 A
Quick shut down	no
Overexcitation time	- s
Temperature range	-20…80°C
Connector type	Spring Clamp
Certification	UL (ab Q2/2022)
Output voltage	Uin x 0,45 V

CONTACT

Sales Team Kendrion Villingen

+49 (0) 7721 877-1417

sales-villingen-ib@kendrion.com

PRODUCT

https://www.kendrion.com/en/productfinder/group/product/electronic-modules-for-brakes/32-07102b53

© Kendrion N.V.