

## ELECTRONIC MODULES FOR BRAKES

### Bridge Rectifier - Slim Collection

32 67103B53

Thanks to its extremely compact design, the overexcitation rectifier can be installed in very restricted space. The module features a central bore for screw fixing inside the terminal box. It can also be installed by using an adhesive pad. These types of Slim Collection AC operate as a half-wave/bridge rectifier with integrated electronic fast turn-off through voltage detection (depending on type).



#### Features

- Very small design
- Cost-effective
- Versatile options for assembly and connection through central hole
- Overexcitation function
- Integrated fast shutdown
- Energy savings up to 75%
- Dimensions (LxWxH): 60x24x19 mm

DESCRIPTION	VALUE
Rectifier type	Bridge Rectifier
Input voltage range	100 bis 240 V
Max. current	0,8 A
Quick shut down	yes
Overexcitation time	- s
Temperature range	-20...80°C
Connector type	Spring Clamp
Certification	UL (ab Q2/2022)
Output voltage	$U_{in} \times 0,89 \text{ V}$

## CONTACT

Sales Team Kendrion Villingen

+49 (0) 7721 877-1417

[sales-villingen-ib@kendrion.com](mailto:sales-villingen-ib@kendrion.com)

## PRODUCT

<https://www.kendrion.com/en/productfinder/group/product/electronic-modules-for-brakes/32-67103b53>