

## ELECTRONIC MODULES FOR BRAKES

### Half-Wave-Rectifier - BEG-261-460-01

13046439

The Regular Collection 6-pole half-wave rectifiers conduce to supply electromagnetic DC-brakes and clutches with half-wave rectified AC voltage. For DC-switching a spark suppressor is integrated via terminals 5 and 6. This significantly reduces the load on the DC-side switching contact and thereby improves its lifetime. The coil power is switched via the switching contact.



DESCRIPTION	VALUE
Rectifier type	Half-Wave-Rectifier
Input voltage range	0 bis 460 V
Max. current	0,75 A
Quick shut down	over contact
Overexcitation time	- s
Temperature range	-40...80°C
Connector type	Screw Terminal
Certification	UL
Output voltage	$U_{in} \times 0,45 V$

## CONTACT

Sales Team Kendrion Villingen

+49 (0) 7721 877-1417

[sales-villingen-ib@kendrion.com](mailto:sales-villingen-ib@kendrion.com)

## PRODUCT

<https://www.kendrion.com/en/productfinder/group/product/electronic-modules-for-brakes/beg-261-460-01>